



172.100 **VONYX**

VPA1500 PA Amplifier 2x 750W Media Player with BT

A series of amplifiers for semi-professional use. Modern technology ensures long-term top performance and connecting to and from this amplifier is a simple task! Like all of Vonyx amplifiers the VPA1500 is built to hold up under pressure. This unit will give you the sound output you need in a crowded club, a stage or in your studio. It can be connected to any standard studio or mobile rack with ease! Suitable for 19" applications.

Playback options : BT streaming, SD, USB
Output channels : 2
Output power: @ 4 Ohm per channel : 750W
Output power: @ 8 Ohm per channel : 500W
Speaker connections : 6.3mm jack, Speaker 2-pin, Speaker screw terminal
Impedance : 4 - 8 Ohm
Output connections : 6.3mm Jack, RCA
Frequency response : 20Hz - 20.000Hz
THD :
Signal-to-noise ratio : >98dB
Input sensitivity line : 775mV - 1.2V
Input impedance : 10 kOhm
Power supply : 220-240VAC 50Hz
Dimensions (L x W x H) : 482 x 270 x 88mm (2U)
Is the item 19" : Yes
Weight : 8,30

- 2x 750W stereo amplifier
- Using BT wireless technology for audio streaming
- Integrated USB, SD/MMC media player
- mediaplayer with MP3 record function
- RCA and 6.3mm Jack inputs
- LED VU for indicating overload
- NL2 speaker connectors, 6.3mm Jack and Terminal outputs
- Aluminum frontpanel and handles
- Suitable for 19" rack mounting (2U)
- Remote control for MP3 player