





PDM660 Condensator Microphone

The PDM660 is a professional cardioid condensator microphone, ideal for speech, vocals and accoustic guitars. With built-in pop filter. Durable metal housing with rubber finish protects it from bumps and falls. The microphone is powered by 48V phantom power.

| Frequency response | 50Hz-10kHz |
|--------------------|----------------------|
| Power | 48 Vdc phantom power |
| Sensitivity | -46+/-2db |
| Impedance | 680 Ohm |
| Lead length | 5m |
| Dimensions | 178 x 49mm |
| Weight | 298g |

- Ideal for speech, vocals and accoustic guitars
- On/Off switch
- Cardioid characteristic
- Powered by 48V phantom powerIncluding High End PD connex XLR cable 5m
- Including microphone holder
- Including thread adaptor to convert 3/8" thread to 5/8" thread
- Supplied in rigid ABS case