





## PDV360MP3 PA Mixer Amplifier 360W/100V 4 zones

The PDV series is a range of fully featured, high power mixer amplifiers with 4 zone outputs, each with separate 6-step volume controls. This series amplifiers features an integral MP3 module with USB and SD Card slot, a FM tuner and internal BT receiver. Mic 1 channel has an override over all inputs and MP3 player. 24V contacts can be connected to a fire alarm panel for emergency evacuation if required. All models are designed with complete protection from overload to avoid any damage. This series of amplifiers is suitable for applications in a bank, town hall, supermarket, school, hotel, restaurant, shopping centre or any other public space.

Output power: RMS: 360W

Frequency Response : 50Hz - 19.000Hz Power Supply : 220-240VAC 50Hz

Dimensions (L x W x H) : 380 x 420 x 88mm

Weight (kg): 13,00

Accessories : Mounting bracket

- PA amplifier with 4 zones, independently selectable and volume controlled
- Integral media player with FM Tuner, USB and SD slot
- BT receiver for audio streaming
- Overload protection
- Chime and Fire alarm over all channels
- Zone volume control over 6 steps
- Bass/Treble control
- 3x mic inputs and 3x line inputs
- Telephone paging
- Bass and treble controls
- 19" Mounting with the brackets possible (2U)
- Emergency operation by 24V battery (not supplied)